
Teletype Error Reports

TTY messages

TTY0000	Failure installing the SDI TTY driver.
TTY0001 x y	Cannot create SDI TTY device number x, group y because the TTY driver has not been installed.
TTY0002 x y	Cannot create TTY device number x, group y because there is not enough memory. Action: Manually INIT, then use LD 17 to delete and recreate this TTY.
TTY0003 x y	Data corruption on TTY device number x. Action: Manually INIT.
TTY0004 x y z	Invalid FDx with SDI device number y, group z.
TTY0005	Cannot create pseudo TTY FD table because there is not enough memory.
TTY0006 x y	Cannot create CPSI TTY device number x, group y because there is not enough memory. Action: Manually INIT, then use LD 17 to delete and recreate this TTY.
TTY0007 x y	MSDL TTY device number x, group y cannot be created because there is no memory for the device descriptor.
TTY0008 x y	MSDL TTY device number x, group y cannot be created because there is no memory for the TTY buffers.
TTY0009 x y z	Invalid FDx with MSDL device number y, group z.
TTY0010	Cannot create Pseudo TTY (PTY) FD table because there is not enough memory.